



[Zoom in Picture](#)

■ Features

- Controls 8 Modbus lines located virtually anywhere via Ethernet or Internet
- LAN interface 10BaseT/100BaseTx Ethernet
- Configuration over WEB Browser
- Supports TCP/IP, DHCP, ICMP, HTTP, DNS
- Supports ART (Automatic Receive Transmit control)
- RS232/485 interface selectable by Software

ModGate 813RM

Quick Link: | [Features](#) | [Overview](#) | [Application](#) | [Hardware](#) | [Interface](#) | [Performance](#) | [Operating Modes](#) | [Power and Environment](#) | [Special Features](#) | [Security](#) | [Ordering Information](#) | [Optional Accessories](#) |

■ Overview

Modgate 813RM is an industrial-strength Modbus-Network gateway for connecting four Modbus lines to a network running TCP/IP. It operates without platform and distance limitation. ModGate 813RM uses Modbus/TCP for communication on the network. The serial ports are configured for Modbus/ASCII or Modbus/RTU, while the serial lines are physically set for RS232 or RS485. The messages received on the network are sent to the serial lines, messages from the serial ports are sent via network. The configuration of ModGate 813RM is done via HTTP. The user interface is based on Web 2.0 to provide an easy handling of the options. Besides typical serial parameters the configuration includes RS232/485 for serial physical parameters. Further a Modbus address mapping table is available, defining a target port for a certain Modbus address. ModGate devices are available with 1 up to 8 serial ports, optional also with WLAN plus Ethernet. Read the [News Article...](#)

■ Application

- Industrial / Factory / Laboratory automation
- Automatic warehouse control system
- Wafer fabrication system
- SCADA system
- Building automation system

■ Hardware

Processor	ARM 9 166 MHz
I/O controller	16C950 or compatible
Memory	16MB SDRAM, 2 MB Flash
Connector type	DSUB 9 male for serial Port RJ45 for Ethernet

[>Back to top](#)

■ Interface

Ethernet interface	Auto-detecting 10BaseT/100BaseTx
Protocols	TCP/IP, DHCP, ICMP, HTTP, DNS
Serial interface	RS232/485 selected by software
No. of port	8, Speed up to 115200 bps
Available Modes	RS232 full duplex RS485 2-wire, half duplex, without echo
Signals	RS232: TxD,RxD, RTS,CTS, DTR,DSR, DCD, RI, GND RS485: 2 wire Data+/-, GND
RS485 Data control	Controlled by ART (Automatic Receive Transmit control)

■ Performance

Speed	Up to 115200 bps
Parity	None, even, odd
Data bits	7, 8
Stop bits	1, 2
IRQ	None
I/O address	None

[>Back to top](#)

■ Operating Modes

Modbus RTU/ASCII	Modbus RTU or Modbus ASCII protocol selected for each serial port individually
DirectMappingMode	Direct mapping of Modbus addresses to serial ports or TCP connections
PromiscuousMode	Mapping of serial ports to TCP connections

[>Back to top](#)

■ Power and Environment

Power requirements	100 - 240V AC 47-63 Hz, 25VA
Dimension	258×149×45 mm ³ (W×L×H) 278×155×46 mm ³ with DB9 connectors and DIN rail mounting kit 19" 1HU Rackmount
Operating Temp	0°C - 55°C
Storage Temp	-20°C – 85°C
Case	SECC sheet metal (1mm)
Weight	1.9kg

[>Back to top](#)

■ Special Features

Installation	Dip switches set a defined temporary IP Address to contact via WEB Browser
Operating mode	Promiscuous Mode Messages received from the network are sent to the serial port, messages from the serial port are sent to the connected network host. Mapped Mode Received messages are scanned for their target address. This address is found in a table, the message is sent to the defined connection (serial or TCP).
Configuration	Configuration over WEB Browser
ART	Automatic Receive Transmit control for RS485
DNS	Domain Name Server support
Serial Interface	Serial Interface configurable by software
Firmware	Firmware update over WEB Browser
LEDs	LEDs for Power, serial Tx, Rx, Ethernet Link, Speed

[>Back to top](#)

■ Security

Password access	Webinterface is password protected. The password can be changed in the Webinterface.
-----------------	--

[>Back to top](#)

■ Ordering Information

Art.No 6702

Product Name ModGate 813RM

Packing list
ModGate 813RM
Power cord
19" mounting kit
CD-ROM with Driver and configuration software
Printed Quick Installation Guide

[>Back to top](#)

■ Optional Accessories

[DK 35A](#) DIN-Rail mounting kit

[>Back to top](#)

■ Full size product image



[>Back to top](#)